


## **®BMPRO**

## **Key Features**



Free downloadable app available at Google Play and iTunes App Store

Use with deep cycle 12V lead acid, AGM, GEL and LiFePO4 batteries

Reliability with Bluetooth communication

Easy DIY installation - no mechanical expertise required

Monitor several house batteries in parallel with one device

Measure up to 300A peak current in and out of the battery with an internal shunt

## **Specifications**

Input Voltage Range	8V to 16V
Voltage Measurement Resolution	< 20 mV
Continuous Current Rating	240A
Current Measurement Range	300A
Current Measurement Resolution	< 150 mA
Overload Protection	(100ms w/out damage) 800A
Monitored Battery Capacity	7Ah to 800Ah
Temp Measurement Range	-20°C to 70°C (@ Battery Terminal)
Dimensions	140mm x 65mm x 18.6mm
Weight	520g

Note: The BatteryCheck is not suitable to be used with engine cranking applications of any type and is not designed for under vehicle bonnet use.

## **BatteryCheckPRO**

BatteryCheckPRO is a wireless battery monitor manufactured by BMPRO. It connects to a range of standard deep cycle batteries and communicates with smartphones via Bluetooth.

BatteryCheckPRO provides real time battery management data that allows users to effectively monitor remaining battery energy via a simple to use free app.

Choose BatteryCheckPRO if you operate microwave, inverter, hair dryer, or have other high current requirements (over 100A). Instantly view volts and amps, time remaining, battery temperature, battery status, state of charge and battery health. BatteryCheckPRO will monitor performance of your battery so you can ensure you'll always have enough power to keep your adventures on track!



For more information and pricing please contact the SPB team on 1300 001 772 or info@spb.net.au



